

NASA/CR—2000-210069



Suspended Patch Antenna Array With Electromagnetically Coupled Inverted Microstrip Feed

Rainee N. Simons
Dynacs Engineering Company, Inc., Brook Park, Ohio

May 2000

The NASA STI Program Office . . . in Profile

Since its founding, NASA has been dedicated to the advancement of aeronautics and space science. The NASA Scientific and Technical Information (STI) Program Office plays a key part in helping NASA maintain this important role.

The NASA STI Program Office is operated by Langley Research Center, the Lead Center for NASA's scientific and technical information. The NASA STI Program Office provides access to the NASA STI Database, the largest collection of aeronautical and space science STI in the world. The Program Office is also NASA's institutional mechanism for disseminating the results of its research and development activities. These results are published by NASA in the NASA STI Report Series, which includes the following report types:

- **TECHNICAL PUBLICATION.** Reports of completed research or a major significant phase of research that present the results of NASA programs and include extensive data or theoretical analysis. Includes compilations of significant scientific and technical data and information deemed to be of continuing reference value. NASA's counterpart of peer-reviewed formal professional papers but has less stringent limitations on manuscript length and extent of graphic presentations.
- **TECHNICAL MEMORANDUM.** Scientific and technical findings that are preliminary or of specialized interest, e.g., quick release reports, working papers, and bibliographies that contain minimal annotation. Does not contain extensive analysis.
- **CONTRACTOR REPORT.** Scientific and technical findings by NASA-sponsored contractors and grantees.

- **CONFERENCE PUBLICATION.** Collected papers from scientific and technical conferences, symposia, seminars, or other meetings sponsored or cosponsored by NASA.
- **SPECIAL PUBLICATION.** Scientific, technical, or historical information from NASA programs, projects, and missions, often concerned with subjects having substantial public interest.
- **TECHNICAL TRANSLATION.** English-language translations of foreign scientific and technical material pertinent to NASA's mission.

Specialized services that complement the STI Program Office's diverse offerings include creating custom thesauri, building customized data bases, organizing and publishing research results . . . even providing videos.

For more information about the NASA STI Program Office, see the following:

- Access the NASA STI Program Home Page at <http://www.sti.nasa.gov>
- E-mail your question via the Internet to help@sti.nasa.gov
- Fax your question to the NASA Access Help Desk at (301) 621-0134
- Telephone the NASA Access Help Desk at (301) 621-0390
- Write to:
NASA Access Help Desk
NASA Center for Aerospace Information
7121 Standard Drive
Hanover, MD 21076

NASA/CR—2000-210069



Suspended Patch Antenna Array With Electromagnetically Coupled Inverted Microstrip Feed

Rainee N. Simons
Dynacs Engineering Company, Inc., Brook Park, Ohio

Prepared for the
Sixth Ka Band Utilization Conference
sponsored by the IIC—Istituto Internazionale delle Comunicazioni
Cleveland, Ohio, May 31–June 2, 2000

Prepared under Contract NAS3-98008

National Aeronautics and
Space Administration

Glenn Research Center

May 2000

Acknowledgement

This work was performed under the task High Performance Printed Antennas and funded by the Cross Enterprise Technology Development Program (CETDP) in code SM.

This report is a preprint of a paper intended for presentation at a conference. Because of changes that may be made before formal publication, this preprint is made available with the understanding that it will not be cited or reproduced without the permission of the author.

Available from

NASA Center for Aerospace Information
7121 Standard Drive
Hanover, MD 21076
Price Code: A03

National Technical Information Service
5285 Port Royal Road
Springfield, VA 22100
Price Code: A03

SUSPENDED PATCH ANTENNA ARRAY WITH ELECTROMAGNETICALLY COUPLED INVERTED MICROSTRIP FEED

Rainee N. Simons
Dynacs Engineering Company, Inc.
2001 Aerospace Parkway
Brook Park, Ohio 44142
Tel: (216) 433-3462
Fax: (216) 433-8705
E-mail: Rainee.N.Simons@grc.nasa.gov

Abstract

The paper demonstrates a four-element suspended patch antenna array, with a parasitic patch layer and an electromagnetically coupled inverted microstrip feed, for linear polarization at K-Band frequencies. This antenna has the following advantages over conventional microstrip antennas: First, the inverted microstrip has lower attenuation than conventional microstrip; hence, conductor loss associated with the antenna corporate feed is lower resulting in higher gain and efficiency. Second, conventional proximity coupled patch antennas require a substrate for the feed and a superstrate for the patch. However, the inverted microstrip fed patch antenna makes use of a single substrate, and hence, is lightweight and low cost. Third, electromagnetic coupling results in wider bandwidth. Details regarding the design and fabrication will be presented as well as measured results including return loss, radiation patterns and cross-polarization levels.

I. INTRODUCTION

Future space borne microwave/millimeter-wave systems for direct data distribution from a low Earth orbiting satellite will require antennas which have high gain, high efficiency, wide bandwidth, low profile, light weight and low cost. At millimeter-wave frequencies conventional microstrip lines suffer from high conductor loss [1], [2]. The high conductor loss impacts the gain and the efficiency of an array antenna with corporate feed. The conductor loss can be reduced by constructing the feed network using low loss transmission media such as, inverted microstrip [1], [2], suspended microstrip [3] and suspended substrate stripline (SSS) [4]. In the past, a suspended patch antenna excited by an electromagnetically coupled inverted microstrip feed at S-Band frequencies has been demonstrated in [5]. Recently, a suspended rectangular/circular patch antennas with electromagnetically coupled inverted microstrip feed for dual polarization/frequency and circular polarization have been demonstrated at K-Band frequencies in [6] and [7], respectively.

In addition, a cavity backed circular aperture antenna with suspended substrate stripline (SSS) feed has been demonstrated at V-Band frequencies [8], [9].

In this paper, a four-element suspended patch antenna array with, a parasitic patch layer on top and electromagnetically coupled to an inverted microstrip feed, for linear polarization is demonstrated at K-Band frequencies. This antenna has the following advantages over conventional microstrip antennas: First, the inverted microstrip has lower attenuation than conventional microstrip; hence, conductor loss associated with the antenna corporate feed is lower resulting in higher gain and efficiency. Second, the inverted microstrip is easier to fabricate, because the strip width is wider for a given characteristic impedance (Z_0) [10]. Third, conventional proximity coupled patch antennas require a substrate for the feed and a superstrate for the patch. However, the inverted microstrip fed patch antenna makes use of a single substrate, and hence, is lightweight and low cost. Fourth, electromagnetic coupling results in wider bandwidth. Details regarding the design and fabrication will be presented as well as measured results, which include return loss, radiation patterns, and cross-polarization levels.

II. ANTENNA CONSTRUCTION

An inverted microstrip line consists of a dielectric substrate (RT/Duroid 5880[®], $\epsilon_{r1} = 2.22$) of thickness h_1 (0.01 inch) separated from a ground plane by an air gap of height g_1 (0.01 inch) as shown in Fig. 1. The strip conductor of width W_i (≈ 0.045 inch for $Z_0 = 50 \Omega$) is situated on the lower surface of the substrate facing the ground plane. A patch antenna is printed on the opposite side of the substrate and electromagnetically coupled to the inverted microstrip feed. A superstrate, of thickness h_2 and dielectric constant ϵ_{r2} equal to 0.01 inch and 2.22 respectively, and with a parasitic patch on the top surface, is placed at a distance g_2 equal to 0.125 inch above the substrate. A schematic of a single-element antenna with a parasitic patch on top, and with an electromagnetically coupled inverted microstrip feed, is shown in Fig. 2. The length L (0.18 inch) and width W (0.31 inch) of both the active and the parasitic patches are identical in the initial experiments. The overlap between the active patch and the feed line is indicated as S . Based on the dimensions of this single-element antenna, a four-element array with inverted microstrip feed network is designed. The feed network is designed according to [11] and has the advantage of requiring fewer and shorter microstrip lines, thereby further reducing the feed loss. The T-junctions in the feed network

are designed according [12]. The center-to-center inter-element spacing is 0.3886 inch along both planes. Figs 3(a) and (b) shows the mask of the feed network and the patch array, respectively.

III. EXPERIMENTAL RESULTS

The measured return loss of the four-element array is shown in Fig. 4. The measurements show that the array is very well matched to the 50 Ω feed lines and the -10.0 dB return loss bandwidth is about 5.4 percent for the initial experiments at K-Band frequencies. The array radiates with a linear polarization perpendicular to the feed. The measured E- and H-plane radiation patterns and the cross-polarization level for the array are shown in Fig. 5. The measured gain of the array as compared to a standard gain horn antenna is estimated to be about 10.0 dB.

IV. CONCLUSIONS

The paper demonstrates a four-element suspended patch antenna array, with a parasitic patch layer and an electromagnetically coupled inverted microstrip feed, for linear polarization at K-Band frequencies. The design, fabrication, and experimental results which include, return loss, E- and H-plane radiation patterns, and cross-polarization level are presented.

REFERENCES

- [1] T. Itoh, "Overview of Quasi-Planar Transmission Lines," *IEEE Trans. Microwave Theory Tech.*, vol. 37, no. 2, pp. 275–280, Feb. 1989.
- [2] B.E. Spielman, "Dissipation Loss Effects in Isolated and Coupled Transmission Lines," *IEEE Trans. Microwave Theory Tech.*, vol. MTT-25, no. 8, pp. 648–656, Aug. 1977.
- [3] J.M. Baracco and A. Carlstrom, "X-Band Microstrip Array Antenna in Suspended Technology," 1997 *IEEE Antennas and Propagation Society Inter. Symp. Dig.*, vol. 2, pp. 1256–1259, 1997.
- [4] E. Rammos, "A Low Tolerance Dual Slot Radiator for Space and Ground Applications," 1991 *IEEE Antennas and Propagation Society Inter. Symp. Dig.*, vol. 3, pp. 1599–1602, 1991.
- [5] Q. Zhang, Y. Fukuoka, and T. Itoh, "Analysis of a Suspended Patch Antenna Excited by an Electromagnetically Coupled Inverted Microstrip Feed," *IEEE Trans. Antennas and Propagation*, vol. AP-33, no. 8, pp. 895–899, Aug. 1985.
- [6] R.N. Simons, "Suspended Rectangular/Circular Patch Antennas with Electromagnetically Coupled Inverted Microstrip Feed for Dual Polarization/Frequency," accepted for presentation at the 2000 *IEEE International Symposium on Antennas and Propagation*, July 16–21, 2000, Salt Lake City, Utah.
- [7] R.N. Simons, "Suspended Patch Antennas with Electromagnetically Coupled Inverted Microstrip Feed for Circular Polarization," accepted for presentation at the 2000 *IEEE International Symposium on Antennas and Propagation*, July 16–21, 2000, Salt Lake City, Utah.

- [8] R.N. Simons, "A Millimeter-Wave Cavity-Backed Suspended Substrate Stripline Antenna," 1999 IEEE Antennas and Propagation Society Inter. Symp. Dig., vol. 3, pp. 2110–2113, 1999.
- [9] D. Chun, R.N. Simons, and L.P.B. Katehi, "Modeling and Characterization of Cavity Backed Circular Aperture Antenna with Suspended Stripline Probe Feed," accepted for presentation at the 2000 IEEE International Symposium on Antennas and Propagation, July 16–21, 2000, Salt Lake City, Utah.
- [10] J. Rivera and T. Itoh, "Analysis of an Electromagnetically Coupled Patch Antenna," 1983 IEEE Antennas and Propagation Society Inter. Symp. Dig., vol. 1, pp. 170–173, 1983.
- [11] M.L. Oberhart, Y.T. Lo and R.Q. Lee, "New Simple Feed Network for an Array Module of Four Microstrip Elements," Electronics Letters, vol.23, no. 9, pp. 436–437, April 1987.
- [12] B.C. Wadell, Transmission Line Design Handbook, Norwood, Massachusetts: Artech House Inc., 1991, p. 315.




Figure 1.—Cross-section showing a suspended patch antenna with a parasitic patch excited by an inverted microstrip line feed.






Figure 2.—Schematic of a patch antenna with a parasitic patch electromagnetically coupled to an inverted microstrip line feed for linear polarization.



(a) (b)

Figure 3.—Mask layout of four element K-Band suspended patch antenna array. (a) Feed network. (b) Patch array.




Figure 4.—Measured return loss of the four element array.




Figure 5.—Co-pol and cross-pol radiation patterns at 22.5 GHz.

REPORT DOCUMENTATION PAGE			<i>Form Approved</i> <i>OMB No. 0704-0188</i>	
Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503.				
1. AGENCY USE ONLY (Leave blank)		2. REPORT DATE May 2000	3. REPORT TYPE AND DATES COVERED Final Contractor Report	
4. TITLE AND SUBTITLE Suspended Patch Antenna Array With Electromagnetically Coupled Inverted Microstrip Feed			5. FUNDING NUMBERS WU-632-6E-51-00 NAS3-98008	
6. AUTHOR(S) Rainee N. Simons				
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) Dynacs Engineering Company, Inc. 2001 Aerospace Parkway Brook Park, Ohio 44135			8. PERFORMING ORGANIZATION REPORT NUMBER E-12247	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES) National Aeronautics and Space Administration John H. Glenn Research Center at Lewis Field Cleveland, Ohio 44135-3191			10. SPONSORING/MONITORING AGENCY REPORT NUMBER NASA CR-2000-210069	
11. SUPPLEMENTARY NOTES Prepared for the Sixth Ka Band Utilization Conference sponsored by the IIC—Istituto Internazionale delle Comunicazioni, Cleveland, Ohio, May 31–June 2, 2000. Rainee N. Simons, Dynacs Engineering Company, Inc., 2001 Aerospace Parkway, Brook Park, Ohio 44135. Project Manager, Dennis Vano, Systems Engineering Division, organization code 7830, (216) 433-2730.				
12a. DISTRIBUTION/AVAILABILITY STATEMENT Unclassified - Unlimited Subject Category: 33 This publication is available from the NASA Center for AeroSpace Information, (301) 621-0390.			12b. DISTRIBUTION CODE	
13. ABSTRACT (Maximum 200 words) The paper demonstrates a four-element suspended patch antenna array, with a parasitic patch layer and an electromagnetically coupled inverted microstrip feed, for linear polarization at K-Band frequencies. This antenna has the following advantages over conventional microstrip antennas: First, the inverted microstrip has lower attenuation than conventional microstrip; hence, conductor loss associated with the antenna corporate feed is lower resulting in higher gain and efficiency. Second, conventional proximity coupled patch antennas require a substrate for the feed and a superstrate for the patch. However, the inverted microstrip fed patch antenna makes use of a single substrate, and hence, is lightweight and low cost. Third, electromagnetic coupling results in wider bandwidth. Details regarding the design and fabrication will be presented as well as measured results including return loss, radiation patterns and cross-polarization levels.				
14. SUBJECT TERMS Suspended patch antenna; Inverted microstrip line; Array antenna; Suspended substrate stripline			15. NUMBER OF PAGES 11	
			16. PRICE CODE A03	
17. SECURITY CLASSIFICATION OF REPORT Unclassified	18. SECURITY CLASSIFICATION OF THIS PAGE Unclassified	19. SECURITY CLASSIFICATION OF ABSTRACT Unclassified	20. LIMITATION OF ABSTRACT	

